Technical Specifications

Power Supply	928VDC SELV
Power Consumption	max. 115mW
Total Power Loss	max. 115mW
Safety Rating	IP40
Capacitive Touch	5 touch points
Ambient Temperature	-2070°C / -4158°F
Temperature Detection Range	-40125°C / -40257°F +/- 0.5°C /0.9°F
Humidity Detection Range	0100% r.H. +/- 2% (non-condensing)
Dimensions	80x80x22mm / 3.15x3.15x0.87" (LxWxH)
Maintenance & Cleaning	This device is free of main- tenance and may only be cleaned with a dry cloth.

Connection

Wire Diameter	0.250.8mm² / AWG23AWG18
Exposed Wire Length	5mm / 0.2"
Push-In-Technology	To make connection, insert the wire; to remove the wire twist and pull at the same time.

LOXONE

No Gimmicks. Real Smart Homes. LOXONE

Need Help?

loxone.com/support



Touch Tree

Loxone Electronics GmbH Smart Home 1 4154 Kollerschlag Austria

loxone.com



Part No: 100221 (White) Part No: 100222 (Anthracite)

About the product


The Loxone Touch has five touch zones, which can be configured according to your needs. The large central touch zone is ideal for controlling lighting, whilst the corner zones are handy for controlling music and blinds, for example.

Features

- · 5 touch buttons
- · Temperature & humidity sensor
- · Optional click feedback

Installation

Install the mounting frame on the desired installation place. Power up the device and pair it with your Miniserver in Loxone Config. To finish the installation attach the Loxone Touch on the mounting frame.



This folder is a part of the product!



For additional information, declaration of confirmity, visit www.loxone.com/help/touch-tree

