

Technical Specifications

Access Possibilities	NFC, Key Code
Power Supply	9...28VDC SELV/PELV
Power Consumption	typ. 0.05W, max. 0.8W (while reading NFC)
Safety Rating	IP44
Ambient Temperature	-20...55°C / -4...131°F
Humidity	95% r.H. (non condensing)
Maintenance & Cleaning	This device is free of maintenance and may only be cleaned with a dry cloth.

Connection

Wire Diameter	0.32...0.08mm ² / AWG22...AWG28
Exposed Wire Length	3.5mm / 0.14"
Push-In Technology	To make connection, insert the wire; to remove the wire twist and pull at the same time.

NEED HELP?

For further information and documentation visit:
www.loxone.com/help/NFC_Code_Touch



LOXONE Smart Home

GET IN TOUCH!

office@loxone.com


www.loxone.com/contact



NFC CODE TOUCH TREE

Part No.: 100300 (white)

Part No.: 100306 (anthracite)



About the product

Get access to your Smart Home with encrypted or unencrypted NFC tags, via your NFC enabled smartphone or through your own unique key code.

Features

- Authentication via encrypted and unencrypted NFC Tags or NFC enabled smartphones or key code
- Supports permanent, disposable or time-limited key codes
- Universal button
- Alarm-authentication

Important Information

- For security reasons, we strongly suggest you only use encrypted NFC tags for access control from Loxone.

Installation

Install the mounting frame of the NFC Code Touch on the desired installation place. Power up the device and pair it with your Miniser- ver in Loxone Config. To finish the installation, attach the NFC Code Touch as shown on the mounting frame.

